

Panasonic NCP: Stappenplan naar Sip.wlvoip.net

1.1 Slot Port Property - Virtual SIP Gateway

No.	Slot	Port	Connection	Channel Attribute	Provider Name (20 characters)	SIP Server Location		SIP Server Port Number	SIP Service Domain (100 characters)	Subscriber Number
						Name (100 characters)	IP Address			
1	1	1	INS	Basic channel	Signet	sip.wlvoip.net		5060	sip.wlvoip.net	
2	1	2	INS	Additional channel for Slot1 Ch1				5060		
3	1	3	INS	Additional channel for Slot1 Ch1				5060		
4	1	4	INS	Additional channel for Slot1 Ch1				5060		
5	1	5	INS	Additional channel for Slot1 Ch1				5060		
6	1	6	INS	Additional channel for Slot1 Ch1				5060		
7	1	7	INS	Additional channel for Slot1 Ch1				5060		
8	1	8	INS	Additional channel for Slot1 Ch1				5060		
9	1	9	Fault	Not Used				5060		
10	1	10	Fault	Not Used				5060		
11	1	11	Fault	Not Used				5060		
12	1	12	Fault	Not Used				5060		
13	1	13	Fault	Not Used				5060		
14	1	14	Fault	Not Used				5060		
15	1	15	Fault	Not Used				5060		
16	1	16	Fault	Not Used				5060		

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX



RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	User Name (64 characters)	Authentication ID (64 characters)	Authentication Password (32 characters)
	1	1	1	INS	Gebruikersnaam	Gebruikersnaam	Wachtwoord
	2	1	2	INS			
	3	1	3	INS			
	4	1	4	INS			
	5	1	5	INS			
	6	1	6	INS			
	7	1	7	INS			
	8	1	8	INS			
	9	1	9	Fault			
	10	1	10	Fault			
	11	1	11	Fault			
	12	1	12	Fault			
	13	1	13	Fault			
	14	1	14	Fault			
	15	1	15	Fault			
	16	1	16	Fault			

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX

RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	Register Ability	Register Sending Interval (s)	Un-Register Ability when port INS	Registrar Server		Registrar Server Port Number
								Name (100 characters)	IP Address	
	1	1	1	INS	Enable	3600	Enable	sip.wlvoip.net		5060
	2	1	2	INS	Enable	3600	Enable			5060
	3	1	3	INS	Enable	3600	Enable			5060
	4	1	4	INS	Enable	3600	Enable			5060
	5	1	5	INS	Enable	3600	Enable			5060
	6	1	6	INS	Enable	3600	Enable			5060
	7	1	7	INS	Enable	3600	Enable			5060
	8	1	8	INS	Enable	3600	Enable			5060
	9	1	9	Fault	Enable	3600	Enable			5060
	10	1	10	Fault	Enable	3600	Enable			5060
	11	1	11	Fault	Enable	3600	Enable			5060
	12	1	12	Fault	Enable	3600	Enable			5060
	13	1	13	Fault	Enable	3600	Enable			5060
	14	1	14	Fault	Enable	3600	Enable			5060
	15	1	15	Fault	Enable	3600	Enable			5060
	16	1	16	Fault	Enable	3600	Enable			5060

1.1 Slot

Port Property - Virtual SIP Gateway

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX



RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	STUN Server		STUN Server Port Number
					Name (100 characters)	IP Address	
	1	1	1	INS	stun.signet.nl		3478
	2	1	2	INS			3478
	3	1	3	INS			3478
	4	1	4	INS			3478
	5	1	5	INS			3478
	6	1	6	INS			3478
	7	1	7	INS			3478
	8	1	8	INS			3478
	9	1	9	Fault			3478
	10	1	10	Fault			3478
	11	1	11	Fault			3478
	12	1	12	Fault			3478
	13	1	13	Fault			3478
	14	1	14	Fault			3478
	15	1	15	Fault			3478
	16	1	16	Fault			3478

OK(O) Cancel(C) Apply(A)

Command(M) Select Provider(S) Add Provider(P)

Main Account Register NAT Option Calling Party Called Party Voice/FAX RTP/RTCP T.38 T.38 Option DSP Supplementary Service

-	No.	Slot	Port	Connection	Session Refresh (Session Timer)			Proxy-Require Option (100 characters)	Diversion Header	Failover Timer(INVITE)	Failover Response (ICMP)
					Session Timer Ability	Session Expire Timer (s)	Refresh Method				
	1	1	1	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	2	1	2	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	3	1	3	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	4	1	4	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	5	1	5	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	6	1	6	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	7	1	7	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	8	1	8	INS	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	9	1	9	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	10	1	10	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	11	1	11	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	12	1	12	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	13	1	13	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	14	1	14	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	15	1	15	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable
	16	1	16	Fault	Enable(Passive)	180	re-INVITE		Disable	0s	Disable

OK(O) Cancel(C) Apply(A)

Command(M) Select Provider(S) Add Provider(P)

Main Account Register NAT Option Calling Party Called Party Voice/FAX RTP/RTCP T.38 T.38 Option DSP Supplementary Service

-	No.	Slot	Port	Header Type	From Header		P-Preferred-Identity Header		Number Format	Remove Digit	Additional Dial	Anonymous format in "From" header	P-Asserted-I-header
					User Part	SIP-URI (100 characters)	User Part	SIP-URI (100 characters)					
	1	1	1	P-Preferred-Identity Header	User Name		PBX-CLIP		National	0		Display name and SIP-URI	Disable
	2	1	2	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	3	1	3	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	4	1	4	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	5	1	5	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	6	1	6	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	7	1	7	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	8	1	8	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	9	1	9	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	10	1	10	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	11	1	11	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	12	1	12	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	13	1	13	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	14	1	14	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	15	1	15	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable
	16	1	16	From Header	User Name		User Name		National	0		Display name and SIP-URI	Disable

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX



RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	Number Format	Type
	1	1	1	INS	National	To header
	2	1	2	INS	National	To header
	3	1	3	INS	National	To header
	4	1	4	INS	National	To header
	5	1	5	INS	National	To header
	6	1	6	INS	National	To header
	7	1	7	INS	National	To header
	8	1	8	INS	National	To header
	9	1	9	Fault	National	To header
	10	1	10	Fault	National	To header
	11	1	11	Fault	National	To header
	12	1	12	Fault	National	To header
	13	1	13	Fault	National	To header
	14	1	14	Fault	National	To header
	15	1	15	Fault	National	To header
	16	1	16	Fault	National	To header

1.1 Slot Port Property - Virtual SIP Gateway

OK(O) Cancel(C) Apply(A)

Command(M) Select Provider(S) Add Provider(P)



Main Account Register NAT Option Calling Party Called Party Voice/FAX RTP/RTCP T.38 T.38 Option DSP Supplementary Service

-	No.	Slot	Port	IP Codec Priority			Packet Sampling Time (G.711A)	Packet Sampling Time (G.711Mu)	Packet Sampling Time (G.729A)	Voice Activity Detection for G.711	Reserved	Inform Annex B Status (G.729A)	Fax Sending Method	Maximum Bit Rate	FAX Detection Ability
				1st	2nd	3rd									
	1	1	1	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	2	1	2	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	3	1	3	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	4	1	4	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	5	1	5	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	6	1	6	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	7	1	7	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	8	1	8	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	9	1	9	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	10	1	10	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	11	1	11	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	12	1	12	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	13	1	13	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	14	1	14	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	15	1	15	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable
	16	1	16	G.711A	G.711Mu	G.729A	20 ms	20 ms	20 ms	Disable	Disable	Disable	G.711 Inband	No Speed Limit	Enable

OK(O) Cancel(C) Apply(A)

Command(M) Select Provider(S) Add Provider(P)

Main Account Register NAT Option Calling Party Called Party Voice/FAX RTP/RTCP T.38 T.38 Option DSP Supplementary Service

-	No.	Slot	Port	Connection	RTP QoS Ability	RTP QoS-ToS Priority	RTP QoS-ToS Type	RTP QoS-DSCP	RTP QoS-HEX	RTCP Packet Sending Ability	RTCP Packet Interval
	1	1	1	INS	ToS	0	Normal			Enable	5 s
	2	1	2	INS	ToS	0	Normal			Enable	5 s
	3	1	3	INS	ToS	0	Normal			Enable	5 s
	4	1	4	INS	ToS	0	Normal			Enable	5 s
	5	1	5	INS	ToS	0	Normal			Enable	5 s
	6	1	6	INS	ToS	0	Normal			Enable	5 s
	7	1	7	INS	ToS	0	Normal			Enable	5 s
	8	1	8	INS	ToS	0	Normal			Enable	5 s
	9	1	9	Fault	ToS	0	Normal			Enable	5 s
	10	1	10	Fault	ToS	0	Normal			Enable	5 s
	11	1	11	Fault	ToS	0	Normal			Enable	5 s
	12	1	12	Fault	ToS	0	Normal			Enable	5 s
	13	1	13	Fault	ToS	0	Normal			Enable	5 s
	14	1	14	Fault	ToS	0	Normal			Enable	5 s
	15	1	15	Fault	ToS	0	Normal			Enable	5 s
	16	1	16	Fault	ToS	0	Normal			Enable	5 s

OK(O)

Cancel(C)



Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main Account Register NAT Option Calling Party Called Party Voice/FAX RTP/RTCP **T.38** T.38 Option DSP Supplementary Service

-	No.	Slot	Port	Connection	T38 FAX Max Datagram	T38 FAX UDPTL Error Correction - Redundancy	T38 FAX UDPTL Redundancy count for T.30 messages	T38 FAX UDPTL Redundancy count for data	T38 FAX Rate Management Method	Reject T.38 Request from Network
	1	1	1	INS	512	Enable	3	0	Transferred TCF	Disable
	2	1	2	INS	512	Enable	3	0	Transferred TCF	Disable
	3	1	3	INS	512	Enable	3	0	Transferred TCF	Disable
	4	1	4	INS	512	Enable	3	0	Transferred TCF	Disable
	5	1	5	INS	512	Enable	3	0	Transferred TCF	Disable
	6	1	6	INS	512	Enable	3	0	Transferred TCF	Disable
	7	1	7	INS	512	Enable	3	0	Transferred TCF	Disable
	8	1	8	INS	512	Enable	3	0	Transferred TCF	Disable
	9	1	9	Fault	512	Enable	3	0	Transferred TCF	Disable
	10	1	10	Fault	512	Enable	3	0	Transferred TCF	Disable
	11	1	11	Fault	512	Enable	3	0	Transferred TCF	Disable
	12	1	12	Fault	512	Enable	3	0	Transferred TCF	Disable
	13	1	13	Fault	512	Enable	3	0	Transferred TCF	Disable
	14	1	14	Fault	512	Enable	3	0	Transferred TCF	Disable
	15	1	15	Fault	512	Enable	3	0	Transferred TCF	Disable
	16	1	16	Fault	512	Enable	3	0	Transferred TCF	Disable

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX



RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	T38 FAX QoS Available	T38 FAX QoS-ToS Priority	T38 FAX QoS-ToS Type	T38 FAX QoS-DSCP	T38 FAX QoS-HEX
	1	1	1	INS	ToS	0	Normal		
	2	1	2	INS	ToS	0	Normal		
	3	1	3	INS	ToS	0	Normal		
	4	1	4	INS	ToS	0	Normal		
	5	1	5	INS	ToS	0	Normal		
	6	1	6	INS	ToS	0	Normal		
	7	1	7	INS	ToS	0	Normal		
	8	1	8	INS	ToS	0	Normal		
	9	1	9	Fault	ToS	0	Normal		
	10	1	10	Fault	ToS	0	Normal		
	11	1	11	Fault	ToS	0	Normal		
	12	1	12	Fault	ToS	0	Normal		
	13	1	13	Fault	ToS	0	Normal		
	14	1	14	Fault	ToS	0	Normal		
	15	1	15	Fault	ToS	0	Normal		
	16	1	16	Fault	ToS	0	Normal		

1.1 Slot

Port Property - Virtual SIP Gateway

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX



RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	Echo Canceller Ability	DSP Digital Gain (Down)	DSP Digital Gain (Up)	EC Gain	NLP Setting
	1	1	1	INS	48 ms	0 dB	0 dB	0 dB	Weak
	2	1	2	INS	48 ms	0 dB	0 dB	0 dB	Weak
	3	1	3	INS	48 ms	0 dB	0 dB	0 dB	Weak
	4	1	4	INS	48 ms	0 dB	0 dB	0 dB	Weak
	5	1	5	INS	48 ms	0 dB	0 dB	0 dB	Weak
	6	1	6	INS	48 ms	0 dB	0 dB	0 dB	Weak
	7	1	7	INS	48 ms	0 dB	0 dB	0 dB	Weak
	8	1	8	INS	48 ms	0 dB	0 dB	0 dB	Weak
	9	1	9	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	10	1	10	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	11	1	11	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	12	1	12	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	13	1	13	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	14	1	14	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	15	1	15	Fault	48 ms	0 dB	0 dB	0 dB	Weak
	16	1	16	Fault	48 ms	0 dB	0 dB	0 dB	Weak

OK(O)

Cancel(C)

Apply(A)

Command(M)

Select Provider(S)

Add Provider(P)

Main

Account

Register

NAT

Option

Calling Party

Called Party

Voice/FAX



RTP/RTCP

T.38

T.38 Option

DSP

Supplementary Service

-	No.	Slot	Port	Connection	CLIP (Receive)	CLIR	CNIP (Send)	CNIP (Receive)	Blind Transfer (REFER)	Attended Transfer (REFER)
	1	1	1	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	2	1	2	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	3	1	3	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	4	1	4	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	5	1	5	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	6	1	6	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	7	1	7	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	8	1	8	INS	P-Asserted-Identity Header	Yes	Yes	No	No	No
	9	1	9	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	10	1	10	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	11	1	11	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	12	1	12	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	13	1	13	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	14	1	14	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	15	1	15	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No
	16	1	16	Fault	P-Asserted-Identity Header	Yes	Yes	No	No	No

